


Selection guide for RCML15

Order key

RCML15-2048/3-6mm-5-1



Note: Special versions are identified with an **-S** at the end of the ordering key. These encoders are configured for customer-specific applications. To be used only after consultation with your distributor. *For special versions, the data in the specific documentation apply, not those in the catalog!*

Selection table

Signal periods per revolution	100, 200, 250, 256, 400, 500, 512, 625, 800, 1000, 1024, 1250, 2000, 2048, 2500, 4000, 4096, 5000		
Commutation	0 2, 3, 4	Without commutation Number of commutation signal periods per revolution (= number of pairs of poles)	
Shaft diameter	Metric Inch	5 mm, 6 mm, 8 mm 1/8+, 3/16, 3/16+, 1/4, 1/4+, 5/16, 3/8, 3/8+	
Voltage supply	5	+5V ±5 %	
Reference mark	1 6 7 8	Width: 90° ±45° elec. Width: 90° ±45° elec. Width: 270° ±45° elec. Width: 270° ±45° elec.	Position: U _{a1} High and U _{a2} High Position: U _{a1} Low and U _{a2} Low Position: U _{a1} High and U _{a2} High Position: U _{a1} Low and U _{a2} Low